





DAC1794 零件表

廠牌 / 名稱	規格	數量
連接座(公)	2.0mm-7P	2
連接座(公)	2.0mm-8P	3
二極體	1N4148	2
ADI	AD797ANZ	4
Texas	OPA134PA	4
NS	LME49710NA	4
IC腳座	8 Pin	12
繼電器	EA2-5	2
排針(公)	2 x 2	6
短路夾		6
磁珠	BEAD	4
精密電阻 1%	1K	2
精密電阻 1%	100R	2
Philips / Dale	10K	2
Philips / Dale	100R	4
Philips / Dale	47.5R	4
Philips / Dale	390R	4
Philips / Dale	1K62	8
Philips / Dale	787R	4
WIMA MKS2	0.1uF	34
WIMA FKP2	1200pF	4
WIMA FKP2	2200pF	4
WIMA FKP2	4700pF	4
WIMA FKP2	100pF	8
Philips / BC	47uF	28
Philips / BC	220uF	8
Philips / BC	10uF	12
	ABF712-3.3V	2
Texas	PCM1794	2
Fairchild	A92	2
電路板		2

DAC1794 Mode Setting

Short JP1	Short JP3	Short JP2	FORMAT	MONO	DF ROLLOFF
3 & 4	3 & 4	3 & 4	I2S	L-channel	Sharp
3 & 4	3 & 4	1 & 2	Left-justified	L-channel	Sharp
3 & 4	1 & 2	3 & 4	Standard, 16-bit	L-channel	Sharp
3 & 4	1 & 2	1 & 2	Standard, 24-bit	L-channel	Sharp
1 & 2	3 & 4	3 & 4	I2S	R-channel	Sharp
1 & 2	3 & 4	1 & 2	Left-justified format	R-channel	Sharp
1 & 2	1 & 2	3 & 4	Standard, 16-bit	R-channel	Sharp
1 & 2	1 & 2	1 & 2	Digital filter bypass	R-channel	Sharp